

**FORNI LINEA START BIG
START BIG LINE OVENS**

Forno elettrico meccanico
Facciata in acciaio inox e corpo
verniciato

Mechanical electric oven
Stainless steel front side and
painted steel body



Il forno elettrico linea START BIG ideale per pizzeria e rosticceria.

Il forno START BIG è un forno semplice e integrato per ottenere il massimo delle prestazioni con un ottimo prezzo.
costruito in acciaio inox e in lamiera preverniciata.
Piano di cottura in pietra refrattaria.
Isolamento in lana di roccia evaporata.
Resistenze corazzate.
Illuminazione interna.
Alimentazione: Volt 230 - Volt 400 Trifase + neutro (a richiesta voltaggi speciali).

The electric oven START BIG line is ideal for pizza and rost foods.

Start BIG oven is a basic oven, conceived to obtain the best performances with a good price l
it is made in stainless steel and coated metal sheet.
Firestone cooking top.
Evaporated mineral wool insulation
Armored resistances. Interior lighting.
Power: 230V, 400V three-phase + neutral (Special voltages on request).



SCHEDA TECNICA FORNI LINEA START BIG

START BIG LINE OVENS DATASHEETS



	START 4 BIG	START 44 BIG	START 6 BIG	START 66 BIG	START 9 BIG	START 99 BIG	START 6 BIG/L	START 66BIG/L
	L P H	L P H	L P H	L P H	L P H	L P H	L P H	L P H
DIMENSIONI INTERNE cm INSIDE DIMENSIONS Inch	72 72 14 28.3 28.3 5.5	72 72 14(x2) 28.3 28.3 5.5(x2)	72 108 14 28.3 42.5 5.5	72 108 14(x2) 28.3 42.5 5.5(x2)	108 108 14 42.5 42.5 5.5	108 108 14(x2) 42.5 42.5 5.5(x2)	108 72 14 42.5 28.3 5.5	108 72 14(x2) 42.5 28.3 5.5(x2)
DIMENSIONI ESTERNE cm OUTSIDE DIMENSIONS Inch	96 98 40 37.7 38.5 15.7	96 98 71 37.7 38.5 27.9	96 134 40 37.7 52.7 15.7	96 134 71 37.7 52.7 27.9	132 134 40 51.9 52.7 15.7	132 134 75 51.9 52.7 29.5	132 98 40 51.9 38.5 15.7	132 98 75 51.9 38.5 29.5
DIMENSIONI IMBALLO cm PACKAGE DIMENSIONS Inch	97 100 56 38.1 39.3 22	97 100 88 38.1 39.3 34.6	97 140 56 38.1 55.1 22	97 140 88 38.1 55.1 34.6	133 135 56 52.3 53.1 22	133 135 88 52.3 53.1 34.6	133 99 56 52.3 38.9 22	133 99 88 52.3 38.9 34.6
CAMERA COTTURA n° BAKING CHAMBER n°	1	2	1	2	1	2	1	2
POTENZA Kw POWER Kw	6.0	12	9.0	18.0	13.0	26.4	9.0	18.0
VOLT	230/400	230/400	400	400	400	400	230/400	230/400
TEMPERATURA C° TEMPERATURE C°	50/500°	50/500°	50/500°	50/500°	50/500°	50/500°	50/500°	50/500°
PESO Kg WEIGHT Kg	94	149	122	199	150	279	122	199
TOTALE PIZZE Ø 36 cm TOTAL PIZZA Ø 36 CM								
N° TEGLIE 60X40 cm N° OF PANS 60X40 cm	1	2	2	4	3	6	2	4
CODICE CODE	7020121004B	7020121044B	7020121006B	7020121066B	7020121009B	7020121099B	7020121006BL	7020121066BL

SCHEDA TECNICA ACCESSORI LINEA START BIG





START BIG LINE ACCESSORIES DATASHEETS



	REFRATTARI CIELO-PLATEA TOP AND BOTTOM REFRACTORY BRICKS	CODICE CODE
	4BIG	7020140001
44BIG	7020140002	
6BIG	7020140003	
66BIG	7020140004	
9BIG	7020140005	
99BIG	7020140006	
6BIG L	7020140007	
66BIG L	7020140008	

SCHEDA TECNICA ACCESSORI LINEA START BIG

START BIG LINE ACCESSORIES DATASHEETS

		DIMENSIONI cm DIMENSIONS Inch 	DIMENSIONI IMBALLO cm PACKAGE DIMENSIONS Inch 	PESO Kg WEIGHT Kg	OPTIONAL OPTIONAL	CODICE CODE
	CAPPA INOX FORNO 4/44 SB OVENS INOX HOOD 4/44 SB	95 102 11,5 37.4 40.1 4.5	99 106 20 38.9 41.7 7.8	11,00		7020120003
	CAPPA INOX FORNO 6/66 SB OVENS INOX HOOD 6/66 SB	95 138 11,5 37.4 54.3 4.5	99 142 20 38.9 55.9 7.8	13,00		7020120004
	CAPPA INOX FORNO 9/99 SB OVENS INOX HOOD 9/99 SB	131 138 11,5 51.5 54.3 4.5	135 142 20 53.1 55.9 7.8	17,00		7020120005
	CAPPA INOX FORNO 6L/66L SB OVENS INOX HOOD 6L/66L SB	131 102 11,5 51.5 40.1 4.5	135 106 20 53.1 41.7 7.8	13,50		7020120006
	MOTORE ELETTRICO ELECTRIC MOTOR					7020130001
	SUPPORTO START 4BIG SUPPORT START 4BIG	101,6 88,1 96 40 34.6 37.7	105 30 20 41.3 11.8 7.8	25,63	/	7020100005
	SUPPORTO START 44BIG SUPPORT START 44BIG	101,6 88,1 86 40 34.6 33.8	105 30 20 41.3 11.8 7.8	24,68	/	7020100007
	SUPPORTO START 6BIG SUPPORT START 6BIG	101,6 124,1 96 40 48.8 37.7	130 30 20 51.1 11.8 7.8	27,57	/	7020100006
	SUPPORTO START 66BIG SUPPORT START 66BIG	101,6 124,1 86 40 48.8 33.8	130 30 20 51.1 11.8 7.8	29,62	/	7020100008
	SUPPORTO START 9BIG SUPPORT START 9BIG	132,6 124,1 96 52.2 48.8 37.7	140 30 20 55.1 11.8 7.8	35,34	/	7020100009
	SUPPORTO START 99BIG SUPPORT START 99BIG	132,6 124,1 86 52.2 48.8 33.8	140 30 20 55.1 11.8 7.8	34,52	/	7020100010
	SUPPORTO START 6BIG L SUPPORT START 6BIG L	132,6 88,1 96 52.2 34.6 37.7	140 30 20 55.1 11.8 7.8	28,88	/	7020100011
	SUPPORTO START 66BIG L SUPPORT START 66BIG L	132,6 88,1 86 52.2 34.6 33.8	140 30 20 55.1 11.8 7.8	27,93	/	7020100012
	KIT TEGLIE START 4BIG TRAYHOLDER KIT START 4BIG	/	100 30 20 39.3 11.8 7.8	5,80	/	7020110006
	KIT TEGLIE START 44BIG TRAYHOLDER KIT START 44BIG	/	100 30 20 39.3 11.8 7.8	5,50	/	7020110007
	KIT TEGLIE START 6BIG TRAYHOLDER KIT START 6BIG	/	130 30 20 51.1 11.8 7.8	6,88	/	7020110008
	KIT TEGLIE START 66BIG TRAYHOLDER KIT START 66BIG	/	130 30 20 51.1 11.8 7.8	6,58	/	7020110009
	KIT TEGLIE START 9BIG TRAYHOLDER KIT START 9BIG	/	140 30 20 55.1 11.8 7.8	6,88	/	7020110008
	KIT TEGLIE START 99BIG TRAYHOLDER KIT START 99BIG	/	140 30 20 55.1 11.8 7.8	6,58	/	7020110009
	KIT TEGLIE START 6BIG L TRAYHOLDER KIT START 6BIG L	/	140 30 20 55.1 11.8 7.8	5,80	/	7020110006
	KIT TEGLIE START 66BIG L TRAYHOLDER KIT START 66BIG L	/	140 30 20 55.1 11.8 7.8	5,50	/	7020110007
	COPPIA ANGOLARI 4BIG - 44BIG - 6BIG L - 66BIG L CORNERS COUPLE 4BIG - 44BIG - 6BIG L - 66 BIG L	/	90 10 10 35.4 3.9 3.9	1,68	/	7020110011
	COPPIA ANGOLARI 6BIG - 66BIG - 9BIG - 99BIG CORNERS COUPLE 6BIG - 66BIG - 9BIG - 99BIG	/	130 10 10 51.1 3.9 3.9	2,04	/	7020110013
	KIT RUOTE CASTORS KIT	/	30 20 20 11.8 7.8 7.8	5,00	/	7020110001

